



Selective Call Rejection

Blocks unwanted calls from disturbing you.

How to use:

Pick up handset and listen for dial tone.

Press *60

Listen for announcement telling you whether the feature is currently on or off. The recorded voice will then tell you how many (if any) numbers are currently stored on your rejection list.

Follow the voice instructions and dial 3 to turn the feature ON (if it is currently off), or OFF (if it is currently on).

To add the last caller to your rejection list:

Press #01#

To hear the phone numbers on your list:

Dial 1

After the list is read, voice instructions will follow.

To add a number to your list:

Press #

Follow the voice instructions you'll hear. You can store up to 31 phone numbers on your rejection list.

To remove a number from your list:

Press *

Follow the voice instructions to remove any or all of those numbers from your rejection list.

To hear the instructions again:

Press 0

When someone calls: If your service is turned ON, callers who are on your rejection list will hear an announcement that your number is not accepting calls at this time. All other calls will ring through as usual.